7 Electrical Parts List

❋ You can search for updated part codes through ITSELF web site.
URL : http://itself. sec. samsung.co.kr

7-1-1 GY15VS* Main PCB Parts

Loc. No.	Code No.	Description	Specification	Remarks
-	BN94-00446B	ASSY PCB MAIN-SN	GY15VS,,,,	SNA
CIS04	0204-001095	THINNER	#4520,-,-,-	SNA
CN105	3701-001219	CONNECTOR-DSUB	15P,3R,FEMALE,ANGLE,AUF	
CN108	3711-004712	CONNECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SN	
CIS07	BN97-00210H	ASSY MICOM	GY15VS,,,,,,,,	SNA
CIS	BN82-00089R	A/S MICOM	GY15VS	SNA
IC102	0903-001266	IC-MICROCONTROLLER	NT68F63,8BIT,PLCC,44P,653MIL,12MHZ,ST,CMOS,PLASTIC,5V,-,0TO+70C,256B,4KB,-,-,MC	
-	BN97-00211B	ASSY SMD-SN	GY15VS,,,,	SNA
BD101	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD102	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD103	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD104	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD105	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD107	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
BD108	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
BD109	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
BD111	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD112	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD113	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD114	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD120	3301-001569	CORE-FERRITE BEAD	AB,600OHM,2.0X1.25X0.9MM,1000MA,TP,NI-CU-ZN,0.1OHM	
BD121	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
C101	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C102	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	
C103	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C104	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-	
C105	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C106	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-	
C107	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C108	2203-000440	C-CERAMIC,CHIP	1nF,10%,50V,X7R,TP,1608,-	
C109	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C110	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C111	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C112	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C113	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C114	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C115	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C116	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C117	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C118	2203-000626	C-CERAMIC,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C119	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C120	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C121	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C122	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C123	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C124	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C125	2203-000626	C-CERAMIC,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C126	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C127	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C128	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	

CONFIDENTIAL

Loc. No.	Code No.	Description	Specification	Remarks
C129	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C130	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C131	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C132	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C135	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C136	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C137	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C138	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C139	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C140	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C141	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C142	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C143	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C144	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C145	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C146	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C147	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C148	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C149	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C150	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C151	2203-005809	C-CERAMIC,CHIP	1000nF,10%,16V,X7R,TP,2012(T1.25)	
C153	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C154	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C155	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C156	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C157	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C158	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C166	2203-000236	C-CERAMIC,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C168	2203-000236	C-CERAMIC,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C169	2203-000315	C-CERAMIC,CHIP	0.12NF,5%,50V,C0G,TP,1608	
C190	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C201	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C202	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
CIS	3704-000001	SOCKET-IC	44P,PLCC,SN,-	
CN101	3711-003161	CONNECTOR-HEADER	BOX,20P,1R,1.25MM,ANGLE,SN,BEG	
CN102	3711-002049	CONNECTOR-HEADER	BOX,6P,1R,1.25mm,SMD-A,SN	SNA
D101	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D102	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D103	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D104	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D105	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
FT101	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
FT102	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
FT103	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
FT104	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
FT105	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
FT106	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
FT107	3301-001145	CORE-FERRITE BEAD	AB,4.5x1.6x1.6mm,-,-	SNA
FT108	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
FT109	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
FT110	3301-001145	CORE-FERRITE BEAD	AB,4.5x1.6x1.6mm,-,-	SNA
IC101	1205-002309	IC-TRANSMITTER	M385,TSSOP,56P,14x6.1mm,PLASTIC,3.3V,,,TP,LVDS	SNA
IC103	1003-001537	IC-LCD CONTROLLER	MST9010,QFP,128P,20X14MM,-,-,TR,PLASTIC,3.3V,-20TO+85C,-,-,-	
IC104	1203-002450	IC-VOLTAGE REGULATOR	MC33375ST-2.5T3,SOT-223,4P,137MIL,PLASTIC,2.475/2.525V,-,-40TO+125C,300MA,-,TP	
IC105	1103-001023	IC-EEPROM	524C80D81,1028x8Bit,SOP,8P,150MIL,10mS,5V,10%,PLASTIC,0to+70C,110uA,CMOS,TP	
IC201	0803-000117	IC-TTL	74F14,INVERTER,SOP,14P,150MIL,	
MP1.0	BN41-00261A	PCB MAIN	GY15V,FR-4,2L,1.0,1.6T,110*72,,4A,,	SNA

CONFIDENTIAL

Loc. No.	Code No.	Description	Specification	Remarks
Q101	0501-002080	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	
Q102	0501-002080	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	
Q103	0501-002080	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	
Q104	0501-002080	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	
Q13	0501-002080	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	
Q132	0505-001170	FET-SILICON	SI9933ADY-T1,P,-20V,3.4A,0.06ohm,2W,SO-8	
R1000	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R1001	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R1002	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R1003	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R1006	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R1009	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R101	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R1010	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R1013	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R112	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R115	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R116	2007-000078	R-CHIP	1Kohm,5%,1/16W,DA,TP,1608	
R117	2007-000078	R-CHIP	1Kohm,5%,1/16W,DA,TP,1608	
R118	2007-000071	R-CHIP	22ohm,5%,1/16W,DA,TP,1608	
R120	2007-000078	R-CHIP	1Kohm,5%,1/16W,DA,TP,1608	
R121	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R122	2007-000071	R-CHIP	22ohm,5%,1/16W,DA,TP,1608	
R123	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R125	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R126	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R127	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R129	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R130	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R131	2007-000092	R-CHIP	15Kohm,5%,1/16W,DA,TP,1608	
R132	2007-000092	R-CHIP	15Kohm,5%,1/16W,DA,TP,1608	
R133	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R134	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R135	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R136	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R137	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R138	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R139	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R140	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R141	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R142	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R143	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R144	2007-000077	R-CHIP	470ohm,5%,1/16W,DA,TP,1608	
R145	2007-000109	R-CHIP	1Mohm,5%,1/16W,DA,TP,1608	
R146	2007-000107	R-CHIP	470Kohm,5%,1/16W,DA,TP,1608	
R147	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R148	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R149	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R150	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R151	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R153	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R154	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R157	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R158	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R159	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R161	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R162	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	

CONFIDENTIAL

Loc. No.	Code No.	Description	Specification	Remarks
R163	2007-000102	R-CHIP	100Kohm,5%,1/16W,DA,TP,1608	
R164	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R165	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R166	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R167	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R169	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R170	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R171	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R172	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R174	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R176	2007-000120	R-CHIP	680ohm,5%,1/16W,DA,TP,1608	
R177	2007-000120	R-CHIP	680ohm,5%,1/16W,DA,TP,1608	
R178	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R179	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R180	2007-000102	R-CHIP	100Kohm,5%,1/16W,DA,TP,1608	
R181	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R182	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R183	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R184	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R185	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R187	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R191	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R192	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R194	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R202	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R203	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R250	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R251	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R292	2007-000078	R-CHIP	1Kohm,5%,1/16W,DA,TP,1608	
R301	2007-000076	R-CHIP	330ohm,5%,1/16W,DA,TP,1608	
R302	2007-000076	R-CHIP	330ohm,5%,1/16W,DA,TP,1608	
R303	2007-000076	R-CHIP	330ohm,5%,1/16W,DA,TP,1608	
R47	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R78	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R79	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R82	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R83	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
RA101	2011-000002	R-NETWORK	22ohm,5%,63mW,L,CHIP,8P,TP	
RA102	2011-000002	R-NETWORK	22ohm,5%,63mW,L,CHIP,8P,TP	
RA103	2011-000002	R-NETWORK	22ohm,5%,63mW,L,CHIP,8P,TP	
RA104	2011-000002	R-NETWORK	22ohm,5%,63mW,L,CHIP,8P,TP	
RA105	2011-000002	R-NETWORK	22ohm,5%,63mW,L,CHIP,8P,TP	
RA106	2011-000002	R-NETWORK	22ohm,5%,63mW,L,CHIP,8P,TP	
U110	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
U111	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
U113	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
U114	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
U115	2901-001114	FILTER-EMI SMD	25VDC,2.0ADC,-,100nF,3.2x1.6x1	
X101	2801-003773	CRYSTAL-SMD	12MHZ,30PPM,28-AAN,20PF,50OHM,TP	
X102	2801-003667	CRYSTAL-SMD	14.3182MHZ,50PPM,28-AAN,16,50OHM,TP	
ZD101	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
ZD102	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
ZD103	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
ZD104	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
ZD105	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	

7-1-2 GY15VS* Others

Loc. No.	Code No.	Description	Specification	Remarks
-	BN90-00490B	ASSY COVER FRONT	GY15VS,,,,	SNA
C/F+C/R	6003-000277	SCREW-TAPTITE	BH,+,B,M3,L12,ZPC(YEL),SWRCH18	SNA
C/F	BN96-00277E	ASSY COVER P-FRONT	GY15VS(S/M153V),ABS HB,WH11,TCO99	SNA
CIS	6003-000259	SCREW-TAPTITE	BH,+,B,M3,L8,ZPC(YEL),SWRCH18A	SNA
CIS	BH68-00035F	LABEL-TCO99	MONITOR,GOYA,PE,T0.05,18.8*16.5,CLEAR	SNA
CIS	BN59-00353A	BOARD-FUNCTION ASSY	GY15VS,CT5000-1170,,FUNCTION ASSY,,144*9,FUNCTION KEY	SNA
CIS	BN63-00560A	COVER-FRONT	GOYA15(153V),ABS HB,WH11	SNA
CIS	BN64-00139A	KNOB-FUNCTION	GOYA17(173V),ABS PC,WH11	
CIS	BN67-00074A	LENS-LED	GOYA17(173V),ACRYL,CLEAR	
-	BN90-00491B	ASSY COVER REAR	GY15VS,,,,	SNA
C/R+STD	6003-001146	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(WHT),SWRCH18A	SNA
C/R	BN96-00278A	ASSY COVER P-REAR	GOYA15(153V),ABS HB ,GR86	
CIS	BN61-00397A	BRACKET-VESA	GOYA 153S,SECC,T1.0,,,,	SNA
CIS	BN63-00561A	COVER-REAR	GOYA15(153V),ABS HB,GR86	SNA
CIS	BN67-00087A	CAP-GATE	GOYA,ABS HB,,,,GR86,	SNA
-	BN90-00492B	ASSY STAND	GY15VS,,,,	SNA
STD	BN96-00281A	ASSY STAND P	GOYA15(153V),ABS HB,WH11	
CIS	6003-000133	SCREW-TAPTITE	BH,+,S,M4,L8,ZPC(YEL),SWRCH18A,-	
CIS	6003-000301	SCREW-TAPTITE	BH,+,S,M4,L6,ZPC(YEL),SWRCH18A	SNA
CIS	6003-001185	SCREW-TAPTITE	FH,+,B,M3,L8,NI PLT,SWRCH18A	SNA
CIS	6003-001188	SCREW-TAPTITE	BH,+,B,M4,L10,YEL,SWRCH18A	SNA
CIS	6502-001088	CABLE CLAMP	DAST-1NB,ID9,T1.5,NYLON66,NTR	SNA
CIS	BN61-00325A	BRACKET-STAND	GOYA15(153V),SECC,T2.0	
CIS	BN61-00341A	BRACKET-BASE	GOYA(153V),SECC,T1.2	
CIS	BN63-00562A	COVER-STAND-BODY	GOYA15(153V),ABS HB,WH11	SNA
CIS	BN63-00564A	COVER-STAND-CAP	GOYA15(153V),ABS HB,WH11	SNA
CIS	BN96-00417A	ASSY MISC P-HINGE	GOYA153V,,,ZN-2 DIE CASTING	SNA
-	BN91-00188A	ASSY LCD-SN	GH15(SN),-,-,	SNA
CIS	BN07-00026A	LCD	LTM150XH-L01,CZB,8BIT,331.6*254.76*12.5,16.19M,-,0.297*0.297,-,-,AMLCD/1 LVDS,-	
CIS	BN81-00013A	A/S PART-LAMP(U)	LTM150XH,LJ91-00250A,-,15XH LAMP(U),-	
CIS	BN81-00013B	A/S PART-LAMP(B)	LTM150XH,LJ91-00251A,-,15XH LAMP(B),-	
-	BN91-00607B	ASSY CHASSIS-SN	GY15VS,,	
CIS	BN44-00081A	ADAPTOR-INVERTER	FSP041-3PI01,15 GOYA,110V/230VAC,50/60HZ,+13V/+5V/+3.3V,2.0A/2.0A/0.1A,42W,110/	SNA
CIS	BN96-00339A	ASSY MISC P-SHIELD DSUB	GOYA153V,,,SPTE T0.5	SNA
CIS	BN63-00573A	SHIELD-D SUB	GOYA15(153V),SPTE,T0.5	
CIS	BN71-00024A	EARTH-PLATE	GH17LS,SUS,T0.15	SNA
-	BN91-00608B	ASSY SHIELD	GY15VS,,,	SNA
CIS	0203-001315	TAPE-CONDUCTOR	DK-K102-30-90,T0.1,W90,L30,GRAY	SNA
CIS	BH39-10339E	CBF POWER CORD	DET,SVT,125V 7A/10A,IVORY,1830	
CIS	BN39-00351A	LEAD CONNECTOR	GY15V,UL1061#28,UL/CSA,20P,80MM,#28,12507HS-20,12507HS-20,BK,1061#28	SNA
CIS	BN63-00563A	COVER-STAND-COVER	GOYA15(153V),ABS HB,IV16	SNA
CIS	BN63-00572A	SHIELD-PCB	GOYA15(153V),SPTE,T0.3	
CIS	BN63-00576A	SHIELD-COVER	GOYA15(153V),SECC ,T0.8	
SH/COV+PAN	6003-000276	SCREW-TAPTITE	BH,+,B,M3,L10,ZPC(YEL),SWCH10	SNA
SH/COV+PI/PCB	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA

CONFIDENTIAL

Loc. No.	Code No.	Description	Specification	Remarks
SH/D_SUB+SH/PCB	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SIGNAL	BN39-00244D	CBF SIGNAL	GY15V,15P/15P,20276-N,1830mm,UL20276,BLACK,D-SUB/MALE,W/O CORE,,DET. TYPE	SNA
-	BN92-00708B	ASSY BOX	GY15VS,,,	SNA
CIS	BH75-10529A	UNIT-HANDLE PACKING	LXA410TLMU,PE,-,WHITE,-	SNA
CIS	BN72-60001A	LEVER TOP	LSD210TL,PE-LD,WHITE,TFT_LCD	SNA
CIS	BN72-60002A	LEVER BOTTOM	LSD210TL,PE-LD,WHITE,TFT-LCD	SNA
CIS	BN68-00134D	LABEL BAR CODE	-,ALL,TCO99,W/W,ART-PAPER 90G,-,WHT,BLACK,-,-,-	SNA
BOX	BN69-00504A	BOX	S/M152V,GUJU,CB-SW4,YEL,A-1,L416*W394*H151	SNA
-	BN92-00709B	ASSY LABEL	GY15VS,,,,	SNA
LABEL	BN68-00404C	LABEL RATING	GH15LS,SS,PE,T0.05,90,45,BLK,POLYESTER,EDC,GY15**	SNA
-	BN92-00710B	ASSY ACCESSORY	GY15VS,,,,	SNA
-	BN92-00711B	ASSY P/MATERIAL	GY15VS,,,,	SNA
P/M	0203-001100	TAPE-OPP MASKING	OPP/W75/CLR,T0.05,W75,L800000,CLR	SNA
P/M	BH69-00256C	PAD-PACKING-EDGE	MV940,B400,W200,L2030,-,-,YEL,-,-	SNA
P/M	BH69-00457B	PACKING-PAD	GH15,FOAM,T3.0,930,1000	SNA
P/M	BH69-30348D	BAG-PE	LDPE,T0.05,W240*L356,Y,-,CMG73	SNA
P/M	BH69-30360A	BAG-AIR	HDPE,T0.2,W1000*L1800,N,-,ALL	SNA
P/M	BH69-40358A	PACKING-PAD TOP(SKD)	CB-SW4,W815*L1154,200G,CQM5307	SNA
P/M	BH69-40379A	PACKING-WRAP	LDPE,W500*T0.02,-,-	SNA
P/M	BN69-00001D	PACKING-PALLET	T541A,WOODEN,1350,830,120	SNA
P/M	BN69-00140V	PAD-PALLET COVER	RB15AS,SW4,1200,3530,-,-,-,-,-	SNA
P/M	BN69-00442A	CUSHION-R/L	GOYA15(153V),EPS,M50	

CONFIDENTIAL

7-2-1 GY17VS* Main PCB Parts

Loc. No.	Code No.	Description	Specification	Remarks
-	BN94-00446A	ASSY PCB MAIN-EJ	GY17VS,,,,	SNA
CIS04	0204-001095	THINNER	#4520,-,-,-	SNA
CIS07	BN61-00161A	GUIDE-POWER	GH17PS,ABS PC,-	SNA
CN102	3711-004712	CONNECTOR-HEADER	BOX,9P,1R,2mm,STRAIGHT,SN	
CN103	3701-001219	CONNECTOR-DSUB	15P,3R,FEMALE,ANGLE,AUF	
PI/PCB+SH/D-SUB	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
CIS06	BN97-00210G	ASSY MICOM	GY17VS,,,,,,,,	SNA
CIS	BN82-00089Q	A/S MICOM	GY17VS	SNA
IC102	0903-001266	IC-MICROCONTROLLER	NT68F63,8BIT,PLCC,44P,653MIL,12MHZ,ST,CMOS,PLASTIC,5V,-,-0TO+70C,256B,4KB,-,-,MC	
-	BN97-00211A	ASSY SMD-EJ	GY17VS,,,,	SNA
BD102	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD103	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD104	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD105	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD107	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD108	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD109	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD110	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
BD111	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
C101	2203-001652	C-CERAMIC,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C102	2203-001652	C-CERAMIC,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C103	2203-001652	C-CERAMIC,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C104	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C105	2402-000179	C-AL,SMD	47uF,20%,16V,GP,TP,6.6x6.6x5.4	
C106	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C107	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C108	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C109	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C110	2203-000626	C-CERAMIC,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C111	2203-000357	C-CERAMIC,CHIP	0.15NF,5%,50V,C0G,TP,1608	
C112	2203-001652	C-CERAMIC,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C116	2203-000626	C-CERAMIC,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C118	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C120	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C121	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C122	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C123	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C124	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C125	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C126	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C127	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C128	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C129	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C130	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C131	2203-000189	C-CERAMIC,CHIP	100nF,+80-20%,25V,Y5V,TP,1608,	
C133	2203-000843	C-CERAMIC,CHIP	39nF,10%,25V,X7R,TP,1608,-	
C134	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C135	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C136	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C137	2203-000236	C-CERAMIC,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C138	2203-000236	C-CERAMIC,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C139	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C140	2203-000888	C-CERAMIC,CHIP	4.7nF,10%,50V,X7R,TP,1608	

CONFIDENTIAL

Loc. No.	Code No.	Description	Specification	Remarks
C141	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C142	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C143	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C144	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C145	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C146	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C147	2203-000888	C-CERAMIC,CHIP	4.7nF,10%,50V,X7R,TP,1608	
C148	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C149	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C150	2203-000236	C-CERAMIC,CHIP	0.1NF,5%,50V,C0G,TP,1608	
C151	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C152	2203-000888	C-CERAMIC,CHIP	4.7nF,10%,50V,X7R,TP,1608	
C153	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C154	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C155	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C157	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C158	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C159	2203-000815	C-CERAMIC,CHIP	0.033NF,5%,50V,C0G,TP,1608	
C161	2203-000815	C-CERAMIC,CHIP	0.033NF,5%,50V,C0G,TP,1608	
C163	2203-000726	C-CERAMIC,CHIP	3.9nF,10%,50V,X7R,TP,1608,-	
C164	2203-000838	C-CERAMIC,CHIP	0.39NF,5%,50V,C0G,TP,1608	
C166	2203-000626	C-CERAMIC,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C168	2203-000626	C-CERAMIC,CHIP	0.022NF,5%,50V,C0G,TP,1608	
C170	2203-005065	C-CERAMIC,CHIP	1000nF,+80-20%,10V,Y5V,TP,1608	
C171	2203-005065	C-CERAMIC,CHIP	1000nF,+80-20%,10V,Y5V,TP,1608	
C172	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C173	2203-005065	C-CERAMIC,CHIP	1000nF,+80-20%,10V,Y5V,TP,1608	
C174	2203-005065	C-CERAMIC,CHIP	1000nF,+80-20%,10V,Y5V,TP,1608	
C175	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C176	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C177	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C178	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C179	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C180	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C181	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C182	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C183	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C184	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C185	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C186	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C187	2203-000280	C-CERAMIC,CHIP	0.01NF,0.5PF,50V,C0G,TP,1608	
C188	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C189	2203-000384	C-CERAMIC,CHIP	0.015NF,5%,50V,C0G,TP,1608	
C193	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	
C194	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	
C195	2203-005065	C-CERAMIC,CHIP	1000nF,+80-20%,10V,Y5V,TP,1608	
C196	2203-005065	C-CERAMIC,CHIP	1000nF,+80-20%,10V,Y5V,TP,1608	
C303	2203-000357	C-CERAMIC,CHIP	0.15NF,5%,50V,C0G,TP,1608	
C401	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C402	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C403	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C404	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C405	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C406	2203-001652	C-CERAMIC,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C407	2402-001042	C-AL,SMD	100uF,20%,16V,GP,TP,6.6x6.6x5.4mm	

Loc. No.	Code No.	Description	Specification	Remarks
C408	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
C409	2203-001652	C-CERAMIC,CHIP	470nF,+80-20%,16V,Y5V,TP,1608	
C410	2203-005437	C-CERAMIC,CHIP	10000nF,+80-20%,10V,Y5V,TP,3216	
C411	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C412	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C413	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C414	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C415	2203-005005	C-CERAMIC,CHIP	100nF,10%,16V,X7R,TP,1608	
C416	2203-000257	C-CERAMIC,CHIP	10nF,10%,50V,X7R,TP,1608	
CIS	3704-000001	SOCKET-IC	44P,PLCC,SN,-	
CN104	3711-002049	CONNECTOR-HEADER	BOX,6P,1R,1.25mm,SMD-A,SN	SNA
CN18	3711-002049	CONNECTOR-HEADER	BOX,6P,1R,1.25mm,SMD-A,SN	SNA
CN401	3711-004070	CONNECTOR-HEADER	BOX,30P,1R,1.25mm,SMD-A,SN	SNA
D101	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D102	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D103	0401-001056	DIODE-SWITCHING	MMBD4148SE,75V,200MA,SOT-23,TP	
D104	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D105	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D106	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D107	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
D108	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
FT101	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
FT102	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
FT107	3301-001145	CORE-FERRITE BEAD	AB,4.5x1.6x1.6mm,-,-	SNA
FT108	3301-001145	CORE-FERRITE BEAD	AB,4.5x1.6x1.6mm,-,-	SNA
IC101	1203-001293	IC-POSI.FIXED REG.	033,TO-252,3P,6.5MIL,PLASTIC,3	
IC104	1103-001023	IC-EEPROM	524C80D81,1028x8Bit,SOP,8P,150MIL,10mS,5V,10%,PLASTIC,0to+70C,110uA,CMOS,TP	
IC105	0505-001170	FET-SILICON	SI9933ADY-T1,P,-20V,3.4A,0.06ohm,2W,SO-8	
IC106	0803-000117	IC-TTL	74F14,INVERTER,SOP,14P,150MIL,	
IC108	1203-001538	IC-POSI.ADJUST REG.	431,SOT-89,3P,-,PLASTIC,2.47/3	
IC109	1003-001551	IC-LCD CONTROLLER	MVP2,PQFP,160P,28x28mm,,-12mA/12mA,TR,PLASTIC,3.3V,,,2.4V/0.4V,MVP2	SNA
IC110	1204-002056	IC-MODULATOR	P2781A-08SR,SOIC,8P,4.92X3.95MM,PLASTIC,3.3V,-,0TO+70C,TP,EMI REDUCTION IC	
IC112	1203-000490	IC-POSI.FIXED REG.	EZ1117,SOT-223,3P,-,PLASTIC,3.235/3.365V,-,0TO+125C,800MA,1.224/1.264V,TP	
IC113	0505-001170	FET-SILICON	SI9933ADY-T1,P,-20V,3.4A,0.06ohm,2W,SO-8	
IC401	1205-002309	IC-TRANSMITTER	M385,TSSOP,56P,14x6.1mm,PLASTIC,3.3V,,,TP,LVDS	SNA
IC402	1205-002309	IC-TRANSMITTER	M385,TSSOP,56P,14x6.1mm,PLASTIC,3.3V,,,TP,LVDS	SNA
L401	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
L402	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
L403	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
L404	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
L405	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
L406	2703-001334	INDUCTOR-SMD	1.5uH,10%,2x1.25x0.85mm	
MP1.0	BN41-00260A	PCB MAIN	GY17V,FR-4,2L,1.0,1.6T,125*110,,2A,,	SNA
Q101	0501-000342	TR-SMALL SIGNAL	KSC1623-Y,NPN,200mW,SOT-23,TP,135-270	
Q102	0501-002080	TR-SMALL SIGNAL	2SC2412K,NPN,200mW,SC-59,TP,120-270	
R101	2007-000309	R-CHIP	10ohm,5%,1/16W,DA,TP,1608	
R102	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R103	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R104	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R105	2007-000113	R-CHIP	33ohm,5%,1/16W,DA,TP,1608	
R106	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R107	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R108	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R109	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R110	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	

CONFIDENTIAL

Loc. No.	Code No.	Description	Specification	Remarks
R111	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R112	2007-000109	R-CHIP	1Mohm,5%,1/16W,DA,TP,1608	
R113	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R114	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R115	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R116	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R117	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R118	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R119	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R120	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R121	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R122	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R123	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R124	2007-000078	R-CHIP	1Kohm,5%,1/16W,DA,TP,1608	
R125	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R126	2007-000084	R-CHIP	4.7Kohm,5%,1/16W,DA,TP,1608	
R127	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R128	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R129	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R130	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R134	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R135	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R136	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R137	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R138	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R139	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R143	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R144	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R145	2007-000078	R-CHIP	1Kohm,5%,1/16W,DA,TP,1608	
R147	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R148	2007-000078	R-CHIP	1Kohm,5%,1/16W,DA,TP,1608	
R149	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R150	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R151	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R152	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R153	3301-001578	CORE-FERRITE BEAD	AB,800HM,1.6X0.8X0.8MM,190MA,TP,D,0.250HM	
R154	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R155	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R156	2007-000122	R-CHIP	1.2Kohm,5%,1/16W,DA,TP,1608	
R157	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R158	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R159	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R160	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R161	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R162	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R163	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R164	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R165	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R166	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R168	2007-000109	R-CHIP	1Mohm,5%,1/16W,DA,TP,1608	
R169	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R170	2007-000074	R-CHIP	100ohm,5%,1/16W,DA,TP,1608	
R171	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R172	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R173	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	

CONFIDENTIAL

Loc. No.	Code No.	Description	Specification	Remarks
R174	2007-000124	R-CHIP	2.2Kohm,5%,1/16W,DA,TP,1608	
R175	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R176	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R178	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R179	2007-001167	R-CHIP	75ohm,5%,1/16W,DA,TP,1608	
R182	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R183	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R307	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R401	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R402	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R403	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R404	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R405	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R406	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R407	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R408	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R409	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R410	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R411	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R412	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R413	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R414	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R415	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R416	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R417	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R418	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R419	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R420	2007-000072	R-CHIP	47ohm,5%,1/16W,DA,TP,1608	
R421	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R502	2007-000077	R-CHIP	470ohm,5%,1/16W,DA,TP,1608	
R519	2007-000078	R-CHIP	1Kohm,5%,1/16W,DA,TP,1608	
R520	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R521	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R522	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R523	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R524	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R526	2007-000070	R-CHIP	0ohm,5%,1/16W,DA,TP,1608	
R527	2007-000090	R-CHIP	10KOHM,5%,1/16W,DA,TP,1608	
R528	2007-000092	R-CHIP	15Kohm,5%,1/16W,DA,TP,1608	
RA101	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA102	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA103	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA104	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA105	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA106	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA107	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA108	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA109	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA110	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA111	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
RA112	2011-001410	R-NETWORK	120OHM,5%,1/16W,L,CHIP,8P,TP	
X301	2801-003773	CRYSTAL-SMD	12MHZ,30PPM,28-AAN,20PF,50OHM,TP	
X501	2801-003773	CRYSTAL-SMD	12MHZ,30PPM,28-AAN,20PF,50OHM,TP	
ZD104	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	
ZD105	0403-000579	DIODE-ZENER	BZX84C5V1,5.1V,5%,200mW,SOT-23	

CONFIDENTIAL

7-2-2 GY17VS* Others

Loc. No.	Code No.	Description	Specification	Remarks
-	BN90-00490A	ASSY COVER FRONT	GY17VS,,,,	SNA
C/F+C/R	6003-000277	SCREW-TAPTITE	BH,+,B,M3,L12,ZPC(YEL),SWRCH18	SNA
C/F	BN96-00279A	ASSY COVER P-FRONT	GOYA17(173V),ABS HB ,WH11	
CIS	6003-000276	SCREW-TAPTITE	BH,+,B,M3,L10,ZPC(YEL),SWCH10	SNA
CIS	BH68-00035F	LABEL-TCO99	MONITOR,GOYA,PE,T0.05,18.8*16.5,CLEAR	SNA
CIS	BN59-00354A	BOARD-FUNCTION ASSY	GY17VS,CT5000-1180,,FUNCTION ASSY,,144*9,FUNCTION KEY	SNA
CIS	BN63-00565A	COVER-FRONT	GOYA17(173V),ABS HB,WH11	SNA
CIS	BN64-00139A	KNOB-FUNCTION	GOYA17(173V),ABS PC,WH11	
CIS	BN67-00074A	LENS-LED	GOYA17(173V),ACRYL,CLEAR	
-	BN90-00491A	ASSY COVER REAR	GY17VS,,,,	SNA
C/R+STD	6003-001146	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(WHT),SWRCH18A	SNA
C/R	BN96-00280A	ASSY COVER P-REAR	GOYA17(173V),ABS HB ,GR86	
CIS	BN61-00377A	BRACKET-VESA	GOYA19(193V),SECC,T1.0	
CIS	BN63-00566A	COVER-REAR	GOYA17(173V),ABS HB,GR86	SNA
CIS	BN67-00087A	CAP-GATE	GOYA,ABS HB,,,,GR86,	SNA
-	BN90-00492A	ASSY STAND	GY17VS,,,,	SNA
STD	BN96-00282A	ASSY STAND P	GOYA17(173V),ABS HB,WH11	
CIS	6003-000129	SCREW-TAPTITE	BH,+,S,M4,L10,ZPC(YEL),SWRCH18	SNA
CIS	6003-000301	SCREW-TAPTITE	BH,+,S,M4,L6,ZPC(YEL),SWRCH18A	SNA
CIS	6003-001136	SCREW-TAPTITE	BH,+,B,M4,L8,ZPC(YEL),SWRCH18A	SNA
CIS	6003-001185	SCREW-TAPTITE	FH,+,B,M3,L8,NI PLT,SWRCH18A	SNA
CIS	6003-001188	SCREW-TAPTITE	BH,+,B,M4,L10,YEL,SWRCH18A	SNA
CIS	6502-001088	CABLE CLAMP	DAST-1NB,ID9,T1.5,NYLON66,NTR	SNA
CIS	BN61-00326A	BRACKET-STAND	GOYA17(173V),SECC,T2.0	
CIS	BN61-00342A	BRACKET-BASE	GOYA(173V),SECC,T1.2	
CIS	BN63-00567A	COVER-STAND-BODY	GOYA17(173V),ABS HB,WH11	SNA
CIS	BN63-00569A	COVER-STAND-CAP	GOYA17(173V),ABS HB,WH11	SNA
CIS	BN96-00284A	ASSY MISC P-HINGE	GOYA17(173V),ZN-2 DIE CASTING	
-	BN91-00388F	ASSY LCD-EJ	GH17AS	SNA
CIS	BN07-00071A	LCD	LTM170EU-L01,GH17LS,1280*1024,17,16.19M,56,0.264*0.264,0~55,5.0,TN,-	
-	BN91-00607A	ASSY CHASSIS-EJ	GY17VS,,	
ADT	BN44-00082A	ADAPTOR-INVERTER	FSP048-3PI01,17 GOYA,110V/230VAC,50/60HZ,+13V/+5V/+3.3V,2.5A/1.5A/0.3A,48W,110/	SNA
CIS	BN63-00574A	SHIELD-D SUB	GOYA17(173V),SPTE,T0.5	
-	BN91-00608A	ASSY SHIELD	GY17VS,,,	SNA
CIS	0203-001311	TAPE-CONDUCTOR	DK-K102-90-50,T0.13,W50,L90,GRAY	SNA
SH/COV+PAN	6001-000131	SCREW-MACHINE	BH,+,M3,L6,ZPC(YEL),SM20C,-	SNA
SH/BRKT+PAN	6001-001692	SCREW-MACHINE	BH,+,M3,L3,ZPC(YEL),SWRCH18A,FP,-	
PI/PCB+SH/BRKT	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SH/COV+FUN/WIRE	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SH/D_SUB+SH/COV	6003-000117	SCREW-TAPTITE	BH,+,B,M3,L6,ZPC(YEL),SWRCH18A	SNA
SIGNAL	BH39-10339E	CBF POWER CORD	DET,SVT,125V 7A/10A,IVORY,1830	
SIGNAL	BN39-00244D	CBF SIGNAL	GY15V,15P/15P,20276-N,1830mm,UL20276,BLACK,D-SUB/MALE,W/O CORE,,DET. TYPE	SNA
CIS	BN39-00358A	LEAD CONNECTOR	GY17V,UL1571#30,UL/CSA,30P,130MM,#30,12507HS-30,FI-X30H,BK,1571#30,SJ02-01-425	SNA
CIS	BN63-00568A	COVER-STAND-COVER	GOYA17(173V),ABS HB,WH11	SNA
CIS	BN63-00571A	SHIELD-PCB	GOYA17(173V),SPTE,T0.8	

CONFIDENTIAL

Loc. No.	Code No.	Description	Specification	Remarks
CIS	BN96-00338A	ASSY MISC P-SHIELD COVER	GOYA173V,,,SECC T1.0	SNA
-	BN92-00708A	ASSY BOX	GY17VS,,,	SNA
BOX	BH75-10529C	UNIT-HANDLE/PACKING	S/M170MP,PE-LD,PE-HD,-,WHITE,-	
CIS	BN72-60001A	LEVER TOP	LSD210TL,PE-LD,WHITE,TFT_LCD	SNA
CIS	BN72-60002C	LEVER BOTTOM	S/M170MP,PE-HD,BLUE	SNA
BOX	BN68-00134D	LABEL BAR CODE	-,ALL,TC099,W/W,ART-PAPER 90G,-,WHT,BLACK,-,-,-	SNA
BOX	BN69-00508A	BOX	S/M172V,GUJU,CB-SW4,YEL,A-1,L448*W442*H176	SNA
-	BN92-00709A	ASSY LABEL	GY17VS,,,,	SNA
LABEL	BN68-00404E	LABEL RATING	GH17MS,SS,PE,T0.05,90,45,BLK,POLYESTER,EDC,GY17**	SNA
-	BN92-00710A	ASSY ACCESSORY	GY17VS,,,,	SNA
-	BN92-00711A	ASSY P/MATERIAL	GY17VS,,,,	SNA
P/M	0203-001100	TAPE-OPP MASKING	OPP/W75/CLR,T0.05,W75,L800000,CLR	SNA
P/M	BH69-00256A	PAD-PACKING-EDGE	MV540,B400,200,2170,-,-,YEL,-,-	SNA
P/M	BH69-00326A	PALLET-PACKING	PN15VT/HT,WOODEN,928,962,120,-,-,-	SNA
P/M	BH69-00457A	PACKING-PAD	GH17,FOAM,T3.0,1180,1130	SNA
P/M	BH69-30348D	BAG-PE	LDPE,T0.05,W240*L356,Y,-,CMG73	SNA
P/M	BH69-30360A	BAG-AIR	HDPE,T0.2,W1000*L1800,N,-,ALL	SNA
P/M	BH69-40375A	TOP-PAD	SW4,W900*L830*H4,LXA410TLMU	SNA
P/M	BH69-40379A	PACKING-WRAP	LDPE,W500*T0.02,-,-	SNA
P/M	BN69-00140K	PAD-PALLET COVER	DV17,SW,900*3390,1165,-,-,-,-,-	SNA
P/M	BN69-00443A	CUSHION-R/L	GOYA17(173V),EPS,M50	

CONFIDENTIAL

Memo